

# exciters/transmitters

- > *easy maintenance series*
- > *compact with integrated exciters series*
- > *high fidelity series*

**TEX1000 LCD**  
**TEX1300 LCD**  
**TEX2000 LCD**



TEX1000-LCD front view

## Features

- > **PRIMARY APPLICATION:** RVR TEX transmitters offer uncompromised transmission quality at a very attractive price. Ideal for use as drivers for mid-power stations or as transmitters in stand-alone applications. Adjustable power output from 0 Watt to maximum output power.
- > **AUDIO PERFORMANCE:** key audio features are low distortion and intermodulation values and a high noise/signal ratio.
- > **HARDWARE FEATURES:** RVR TEX transmitters are compact and indeformable thanks to the stainless steel chassis, in 3 rack units only.
- > **RELIABILITY/CONTINUITY:** dual, redundant power supply ensures limited-power operation in the event of a failure for maximum business continuity. APC (Automatic Power Control) and Foldback protection ensure reliable operation under any operating conditions.
- > **EASE OF MAINTENANCE:** advanced module engineering ensures extreme ease of access and simple maintenance.
- > **INTERFACE CONTROL:** total control thanks to microprocessor easily programmed from menu or via RS232 with all key parameters displayed on LCD.
- > **INPUT/OUTPUT INTERFACE:** built-in high-performance stereo coder, L&R analogue audio inputs, Mono inputs, MPX composite signal and auxiliary inputs for SCA / RDS signals.
- > **REMOTE CONTROL:** built-in telemetry system with GSM modem, battery and battery charger (option).
- > **REGULATORY COMPLIANCE:** state-of-the-art technology in full compliance with EC, FCC and CCIR standards.
- > **USER-FRIENDLY FEATURES:** pushbuttons for user/device interaction provide enhanced accessibility, resulting in extreme ease of use. Configuration software offers a simple, intuitive interface.

**stereo/MPX FM exciters 87,5 - 108 MHz**

*(Oirt and  
JPN Band  
upon  
request)*

exciters/transmitters



TEX1000-LCD rear view

### Caratteristiche

- > **PRIMARY APPLICATION:** i trasmettitori della linea **TEX RVR** sono sinonimo di qualità di trasmissione senza compromessi ad un prezzo estremamente contenuto. Ideali come driver per stazioni di media potenza o come trasmettitori in applicazioni stand-alone. Potenza di uscita regolabile da 0 Watt alla massima potenza erogabile.
- > **AUDIO PERFORMANCE:** le caratteristiche audio di rilievo di questi apparati sono i bassi valori di distorsione, di intermodulazione e l'alto rapporto segnale rumore.
- > **HARDWARE FEATURES:** i **TEX RVR** sono compatti e indeformabili perchè realizzati in chassis di acciaio inox, in sole 3 unità rack.
- > **RELIABILITY/CONTINUITY:** massima continuità di esercizio per la presenza di un doppio alimentatore ridondante che in caso di guasto garantisce comunque il funzionamento dell'apparato a potenza ridotta. Funzionamento in qualsiasi condizione di lavoro, assicurato dal controllo automatico APC e la protezione di Foldback.
- > **EASE OF MAINTENANCE:** estrema accessibilità e semplicità di manutenzione grazie ad una avanzata ingegnerizzazione modulare dell'apparato.
- > **INTERFACE CONTROL:** controllo completo basato su di un micro-processore facilmente programmabile da menu o via RS232 con lettura su display LCD di tutti i parametri principali.
- > **INPUT/OUTPUT INTERFACE:** stereo coder integrato ad elevate prestazioni, ingressi audio analogici L&R, Mono e segnale composto MPX ed ausiliari per segnali SCA / RDS.
- > **REMOTE CONTROL:** sistema di telemetria integrato con modem GSM, batteria e caricabatteria (versione vendibile opzionalmente).
- > **REGULATORY COMPLIANCE:** tecnologia moderna e pienamente rispondente alle normative EC, FCC ed CCIR.
- > **USER-FRIENDLY FEATURES:** estrema semplicità d'utilizzo, data dall'accessibilità fornita dai tasti a pressione per l'interazione fra l'utente e l'apparato. Interfaccia del software di configurazione intuitiva e semplificata.

# exciters/transmitters

- > easy maintenance series
- > compact with integrated exciters series
- > high fidelity series

## Technical specifications

Parameters	TEX1000LCD	TEX1300LCD	TEX2000LCD
<b>GENERALS</b>			
Rated output power	1000W	1300W	2000W
Frequency range	FCC -CCIR and other on request		
Operational Mode	Mono, Stereo, Multiplex		
Modulation type	F3E		
Primary Power	230VAC ±15% or 115VAC		230VAC ±15%
AC Power Consumption	1690 VA / 1660 W / PF: 0,98	2108 VA / 2065W / PF: 0,98	3320 VA / 3300 W / PF:0,99
Overall efficiency	60%	63%	61%
Physical Dimensions (W x H x D)	483 x 132 x 670 mm		
Weigh	27 kg		32 kg
Environmental Working Conditions	-10 ÷ +50 °C / 95% relative Humidity non condensing		
Cooling	Forced, with internal fan		
Frequency programmability	From software, with 10 kHz steps		
Frequency stability	±1 ppm		
Pre-emphasis mode	0/50 (CCIR) µS, 75 (FCC) µS		
Spurious & harmonic suppression	<75 dBc (80 typical)		
Asynchronous AM S/N ratio	≥60 dB (typical 68)		
Synchronous AM S/N ratio	≥50 dB (typical 58)		
<b>MONO OPERATION</b>			
S/N FM Ratio	> 80 dB RMS (typical 83 dB)		
Frequency Response	< ± 0.5 dB 30Hz ÷ 15kHz (typical ± 0.2 dB)		
Total Harmonic Distortion	< 0.1 % 30 Hz ÷ 15 kHz (typical 0.07 %)		
Intermodulation distortion	< 0.02 % with 1 kHz and 1,3 kHz tones		
<b>MPX OPERATION</b>			
Composite S/N FM Ratio	> 80 dB RMS (typical 83 dB)		
Frequency Response	± 0.2 dB 30Hz ÷ 53kHz / ± 0.5 dB 53kHz ÷ 100 kHz		
Total Harmonic Distortion	< 0.1% 30Hz ÷ 53kHz		
Intermodulation distortion	< 0.05% with 1 kHz and 1,3 kHz tones		
<b>INTERNAL STEREO CODER OPERATION</b>			
Stereo S/N FM Ratio	> 75 dB RMS (typical 77dB)		
Frequency Response	± 0.5 dB 30 Hz ÷ 15 kHz		
Total Harmonic Distortion	< 0.05% 30 Hz ÷ 15 kHz		
Intermodulation distortion	≤0.03% with 1 kHz and 1,3 kHz tones		
Stereo separation	> 50 dB 30 Hz ÷ 15 kHz (typical 55 dB)		
<b>AUDIO INPUT CONNECTORS</b>			
Left / Right	XLR balanced; Impedance: 10 k or 600 ohm; Level: -13 to +13 dBu		
MPX unbalanced/RDS	BNC unbalanced; Impedance: 10 k or 50 ohm; Level: -13 to +13 dBu		
SCA/RDS	2 x BNC unbalanced; Impedance: 10 k; Level: -8 to +13 dBu		
<b>OTHER CONNECTORS</b>			
RF Output	7/8" EIA flange type		
RF Monitor	BNC (- 30dBm referred to RF output )		
Pilot output	BNC (1Vpp)		
Interlock Input	BNC		
<b>STANDARD COMPLIANCE</b>			
Safety	EN 60215:1989 EN60215/A1:1992-07 EN60215/A2:1994-09		
EMC	EN 301 489-1 V1.4.1 (2002-08) EN 301 489-11 V1.2.1 (2002-11)		
Radio	EN 302 018-2 V1.2.1 (2005-06)		

All pictures are RVR's property and they are only indicative and not binding. The pictures can be modified without notice.  
These are general specifications. They show typical values and are subject to change without notice.

CE 99/5/CE Revision: 03/09

# exciters/transmitters

## Ordering information

### Options for TEX-LCD - Opzioni per TEX-LCD

Code	Description
/CW	Morse-coded station ID code generated through FSK (Frequency Shift Keying) function * <i>Codice identificativo della radio via codice Morse attraverso la funzione FSK (Frequency Shift Keying) *</i>
/CNT7/8-245	7/8" output RF connector <i>Connettore RF di uscita 7/8"</i>
/CNT7/8-295	7/8" output RF connector ** <i>Connettore RF di uscita 7/8" **</i>
TCPIPINT-TEX	Telemetry system via the Internet <i>Sistema di telemetria attraverso internet</i>
/TLM-TEX3HE	Telemetry system via internal GSM modem. Battery and battery changer included <i>Sistema di telemetria attraverso modem GSM interno. Batteria e caricabatterie incluse</i>
/TLC-TEX3HE	Internal telemetry system without GSM modem <i>Sistema di telemetria interna senza modem GSM</i>
/MODGSM	Telemetry system via internal GSM modem <i>Sistema di telemetria attraverso modem GSM interno</i>
/MODPSTN	Telemetry system via internal PSTN modem <i>Sistema di telemetria attraverso modem PSTN interno</i>
TELINK-C1	Telemetry interface ANTLAN/BURK protocol <i>Interfaccia di telemetria protocollo ANTLAN/BURK</i>
TELINK-SNMP2	Telemetry interface RVR/SNMP 1 HE <i>Interfaccia di telemetria RVR/SNMP</i>

\* Please specify station name on order.

\* *Si prega di specificare il nome della stazione in fase di ordine d'acquisto.*

\*\* Available for model TEX2000LCD

\*\* *Disponibile per il modello TEX2000LCD*



**RVR Elettronica S.p.A.**  
Via del Fonditore, 2/2c  
Zona Industriale Roveri • 40138 Bologna • Italy  
Phone: +39 051 6010506 • Fax: +39 051 6011104  
e-mail: info@rvr.it • web: <http://www.rvr.it>

ISO 9001:2000 certified since 2000



Member of CISQ Federation

**RINA**  
ISO 9001:2000  
Certified Quality System

